
INKER & MASOR

MODEL VC-2 The Verifier

Verifies Accuracy of Voltmeters



Connect to your voltmeter to ensure your meter is in calibration.

Features:

Very Accurate Voltage <u>Output</u> 1mV, 10mV, 100mV, 1v, 2.5v & 5v Use with any manufacturers voltmeter Annual calibration cycle



AVAILABLE FROM STOCK!

Distributed by



The VC-2 works with any manufacturers voltmeter to verify accuracy.

www.teststations.com

www.tinker-rasor.com Info@tinker-rasor.com

www.detectron.com



Tinker & Rasor quality is found in our products, our people and our customer service.



PRODUCT DATA SHEET

MODEL VC-2 VERIFIER

Features:

- · Portable, battery operated
- Highly accurate DC Output
- Verify any DC Voltmeter
- Battery test LED

Applications:

· Verify voltmeter readings

Recommendations:

Use with T&R Models CPV-2 and CPV-4

Use with any DC voltmeter

Environment:

-10°C to 50°C (14°F to 122°F)

Specifications:

OUTPUTS:

0.001v (+/- 1mV)

0.01v (+/-1mV)

0.1v (+/- 1mV)

1.0v (+/- 5mV)

2.5v (+/- 5mV)

5.0v (+/- 5mV)

(6) "AA" cell alkaline batteries

Dimensions:

6.25" x 4" x 2.5", 1.5lbs

(158mm x 101mm x 63mm, 0.7kg)

Shipping Dimensions:

4.5" X 4.5" x 5.75", 3 lbs

(114.3mm x 114.3mm x 146mm, 1.4kg)

DELIVERY: Immediately from STOCK

F.O.B. San Bernardino, CA USA

SERVICE: 24-hour Turn-Around

TERMS: Net30 Days, on approval of credit

WARRANTY: 90 Days, parts and labor



Easy to use

Comes with cables
Annual Calibration recommended



Shown in operation with CPV-4 Voltmeter

AVAILABLE FROM STOCK