
INKER & RASOR



MODEL TriStar 50 AMPS GPS Current Interrupter

Features:

50 Amps (6,000 Watts)
GPS Timing for sync with others
0.005s to 999.999s cycle range
Cable Storage in case
115v - 230v AC power
Removable magnetic antenna
10 Program memory
Non polarity connections



AVAILABLE FROM STOCK!

Distributed by

All T&R Current Interrupters come complete in one unit with all necessary accessories included, and storage for cables inside the case.

There is nothing else to buy or needed to interrupt a rectifier.

www.teststations.com

www.tinker-rasor.com Info@tinker-rasor.com

www.detectron.com



Tinker & Rasor quality is found in our products, our people and our customer service.

INKER & MASOR

CORROSION MITIGATION INSTRUMENTATION

PRODUCT DATA SHEET

MODEL TriStar 50 Amp GPS Interrupter

Features:

- Interrupt up to 50 Amp @ 120 Volt (6,000 watt Max.)
- GPS Timing for Synchronization with other units
- Cycle between 000.005s and 999.999s
- 115v 230v Auto sensing AC power supply
- Removable magnetic mount GPS Antenna
- Manual Sync feature
- 10 Program memory
- Transfer program information to multiple units
- Internal cable storage
- Secure with lid open or closed
- · All connections made from outside of case
- Keypad operation with large LCD screen

Construction:

- Rugged carrying case design for rough field use.
- Sealed against dust and water (not immersion)
- Solid state circuitry, no mercury relays
- Reinforced locking rings, lock with lid open or closed
- · Internal storage of cables

Applications:

- CIPS
- DCVG
- CP Monitoring
- Pipe to Soil Potentials
- Interrupt Ground beds

Specifications:

50 Amp max, AC or DC 120 Volt max, AC or DC Display: 0°C to 50°C (32°F to 122°F) Powered from 115v or 230v (60/50 cycle) AC

Dimensions:

10.62" x 9.68" x 6.87", 15 lbs (269.79mm x 245.87mm x 174.50mm, 6 kg) **Shipping Dimensions:**

11" x 7.5" x 10.5", 16 lbs

(279.40mm x 190.50mm x 266.70mm, 7 kg)

DELIVERY: Immediately from STOCK

F.O.B. San Bernardino, CA USA

SERVICE: 24-hour Turn-Around

TERMS: Net30 Days, on approval of credit

WARRANTY: 90 Days, parts and labor



MODEL TriStar GPS Current Interrupter

AVAILABLE FROM STOCK